MIX6USB

00122

Description

DJ mixer, 6 channels, 2DJ Mic, 1USB.

Features

- A compact and robust 19” DJ-mixer with stylish black design (blue and white LEDs)
- 4 input channels equipped with smooth dual-rail 60mm DJ-faders: 7 line or 5line + 2phonos, 1USB
- 2 separate DJ mics with 3band equalizer, on-air switch and adjustable talkover
- 1 Bidirectional USB sound card (play and record at the same time!)
- Separate 3.5mm stereo input on front panel: easy to connect MP3-player etc.
- Gain, treble, mid, bass controls and peak indicator on all channels
- Assignable smooth 45mm dual-rail crossfader with adjustable curve and on/off switch
- 2 Master outputs, master1 with balanced XLR outputs
- LED VU-meters with CUE/master compare function.
- Pre-fade listening with cue mix and blend/split options
- Free recording software available : Audacity : http://www.audacityteam.org/







Beglec NV has the right to change products and specifications with and without notice. Major as well as minor changes can be involved. This leaflet can contain errors, therefore we advice to consult your local dealer to ensure that actual features and specifications match your requirements. Copyright © 2015 by BEGLEC NV. All rights reserved.

JBSYSTEMS

Specifications

General : Application	Commercial lighting, DJ & Club, Stage & Rental
General : Dimensions (cm)	48.3 x 17.9 x 10.4 cm
General : Weight (kg)	5.02
General : Powerinput	AC 230V, 50Hz
General : Energy Label	No
General : Power consumption W	20
General : Color	black
General : Display	none
General : Fixation	19" rack mountable
General : RU	4U
Audio : min. frequency (Hz)	20
Audio : max. frequency (Hz)	20000
Audio : S/N ratio (> dB)	77
Audio : sensitivity (dB 1W/1m)	No
Audio : supported audio formats	No
Audio : supported audio media	No
Audio : max. output channels	6
Connections : input	No
Connections : output	3-Pin XLR, RCA
Connections : XLR 3 pin	Yes
Connections : XLR 5 pin	No
Connections : rca	Yes
Connections : jack	Yes
Connections : Power Conn.	No
Connections : midi	No
Connections : usb	Yes
Connections : wifi	no
Connections : bluetooth	No
Function : equalizer	Yes
Function : sound effects	No
EANCode	5420025601221
Discontinued	No

Specifications

Power Supply:	AC 230V~ 50Hz
Power consumption:	ON = 20W, OFF = 0W
Fuse:	20mm glass fuse 250V 500mA slow
Frequency response:	20Hz-20kHz (±1.0 dB)
THD + noise:	
S/N Ratio (IHF-A):	>77dB
Sensitivity:	
- Micro inputs:	0.0775mV @ 34kΩ
- Line/CD inputs:	775mV @ 3.6kΩ
- Phono inputs:	0.0775mV @ 31kΩ
Max. Record output:	1V @ 600Ω
Max. Master output:	5V @ 4.7kΩ unbal.
Max. Master output:	2.5V @ 600Ω bal.
Tone controls CH1-CH4:	
	- +10dB/-12dB @ 10kHz
	- +12dB/-24dB @ 1,3kHz
	- +12dB/-29dB @ 50Hz
Tone controls MIC:	
	- +16dB/-16dB @ 10kHz
	- +12dB/-12dB @ 2,5kHz
	- +15dB/-15dB @ 70Hz
Headphone:	120mW@75Ω
Dimensions:	483(W) x 179(H) x 104(D)mm (19" / 4U)
Mounting depth :	85mm
Weight:	3,2kg

www.jb-systems.eu | https://www.facebook.com/JBS.Belgium/

Beglec NV has the right to change products and specifications with and without notice. Major as well as minor changes can be involved. This leaflet can contain errors, therefore we advice to consult your local dealer to ensure that actual features and specifications match your requirements. Copyright © 2015 by BEGLEC NV. All rights reserved.